



EP-61EXA-A

**A Pentium® II Processor based AGP
mainboard**

TRADEMARK

All products and company names are trademarks or
registered trademarks of their respective holders.

*These specifications are subject to change without
notice.*

*Manual Revision 1.1
February 10, 1998*

EP-61EXA-A

Technical Support Services

If you need additional information, help during installation or normal use of this product, please contact your retailer. If your retailer can not help, you may E-Mail us with any questions at the following address tech@epox.com

Record your serial number before installing your EP-61EXA-A mainboard. (the serial number is located near the ISA slots at the edge of the board)

EPoX EP-61EXA-A serial number:

BIOS Upgrades

Please use either our Web Site or BBS for current BIOS Upgrades.

Internet Access

<http://www.epox.com>
sales@epox.com
tech@epox.com

Modem Access

886-2-2247-2742 (Taiwan)
31-182-618451 (The Netherlands)

You can access this number via a Hayes-compatible modem with a 2,400 to 28,800 baud rate. The following setup format is required:

8 Data Bits, No Parity, 1 Stop Bit.

If your modem is unable to connect at higher baud rates, try connecting at 2,400 baud before contacting Technical Support.

Thank you for using EPoX mainboards!

© Copyright 1997 EPoX Computer Company. All rights reserved.

EPoX

User Notice

No part of this product, including the product and software may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language in any form by any means without the express written permission of EPoX Computer Company (hereinafter referred to as EPoX) except documentation kept by the purchaser for backup purposes.

EPoX provides this manual "as is" without warranty of any kind, either express or implied, including but not limited to the implied warranties or conditions of merchantability or fitness for a particular purpose. In no event shall EPoX be liable for any loss or profits, loss of business, loss of use or data, interruption of business or for indirect, special incidental, or consequential damages of any kind, even if EPoX has been advised of the possibility of such damages arising from any defect or error in the manual or product. EPoX may review this manual from time to time without notice. For updated BIOS, drivers, or product release information you may visit EPoX's home page at <http://www.epox.com>

Products mentioned in this manual are mentioned for identification purposes only. Product names appearing in this manual may or may not be registered trademarks or copyrights of their respective companies.

The product name and revision number are both printed on the mainboard itself.

Handling Procedures

Static electricity can severely damage your equipment. Handle the EP-61EXA-A and any other device in your system with care and avoid unnecessary contact with system components on the mainboard.

Always work on an antistatic surface to avoid possible damage to the motherboard from static discharge.

We assume no responsibility for any damage to the EP-61EXA-A mainboard that results from failure to follow installation instructions or failure to observe safety precautions.




Table of Contents

Section 1	Introduction	
	Components Checklist	1-1
	Overview	
	Pentium II	1-2
	S.E.C. Cartridge Terminology	1-3
	Accelerated Graphics Port	1-4
	Hardware Monitoring	1-4
	Desktop Management Interface	1-4
	EP-61EXA-A Form-Factor	1-5
	I/O Shield Connector	1-6
	Power-On/Off (Remote)	1-6
	System Block Diagram	1-7
Section 2	Features	
	EP-61EXA-A Features	2-1
Section 3	Installation	
	EP-61EXA-A Detailed Layout	3-1
	Easy Installation Procedure	
	Configure DIP Switch	3-2
	System Memory Configuration	3-3
	Installing a Pentium® II Processor	3-6
	Device Connectors	3-8
Section 4	Award BIOS Setup	
	BIOS Instructions	4-1
	Standard CMOS Setup	4-2
	BIOS Features Setup	4-3
	Chipset Features Setup	4-8
	Power Management Setup	4-13

PNP/PCI Configuration	4-17
Load Setup Defaults	4-19
Integrated Peripherals	4-19
Change Supervisor or User Password	4-24
IDE HDD Auto Detection	4-24
HDD Low Level Format	4-27
Save & Exit Setup	4-27
Exit Without Saving	4-27

Section 5 *DMI*

DMI Access	5-1
------------------	-----

Section 7 *Appendix*

Appendix A

Memory Map	A-1
I/O Map	A-1
Timer & DMA Channels Map	A-2
Interrupt Map	A-2
RTC & CMOS RAM Map	A-3

Appendix B

POST Codes	A-4
Unexpected Errors	A-7


Appendix C

Load Setup Defaults	A-8
---------------------------	-----

Section 1 INTRODUCTION

Components Checklist

- ✓ A. (1) EP-61EXA-A mainboard
- ✓ B. (1) EP-61EXA-A user's manual
- ✓ C. (1) Floppy ribbon cable
- ✓ D. (1) Hard drive ribbon cable
- E. (1) Heatsink Support Unit (optional)
- F. (1) PS/2 to AT keyboard connector adapter (optional)
- ✓ G. (1) Bus master drivers
- H. (1) DMI (optional)
- I. (1) Audio drivers (optional)



Overview

Pentium II

The Pentium® II Processor is the follow-on to the Pentium® Processor. The Pentium® II Processor, like the Pentium® Pro processor, implements a Dynamic Execution micro-architecture -- a unique combination of multiple branch prediction, data flow analysis, and speculative execution. This enables the Pentium® II Processor to deliver higher performance than the Pentium® processor, while maintaining binary compatibility with all previous Intel architecture processors.

A significant feature of the Pentium® II Processor, from a system perspective, is the built-in direct multiprocessing support. In order to achieve multiprocessing, and maintain the memory and I/O bandwidth to support it, new system designs are needed. For systems with dual processors, it is important to consider the additional power burdens and signal integrity issues of supporting multiple loads on a high speed bus. The Pentium® II Processor card supports both uni-processor and dual processor implementations.

The Pentium® II Processor utilizes Single Edge Contact (S.E.C.) (Figure 1) cartridge packaging technology. The S.E.C. cartridge allows the L2 cache to remain tightly coupled to the processor, while maintaining flexibility when implementing high performance processors into OEM systems. The second level cache is performance optimized and tested at the cartridge level. The S.E.C. cartridge utilizes surface mounted core components and a printed circuit board with an edge finger connection. The S.E.C. cartridge package introduced on the Pentium® II Processor will also be used in future Slot 1 processors.

The S.E.C. cartridge has the following features: a thermal plate, a cover and a PCB with an edge finger connection. The thermal plate allows standardized heatsink attachment or customized thermal solutions. The thermal plate enables a reusable heatsink to minimize fit issues for serviceability, upgradeability and replacement. The full enclosure also protects the surface mount components. The edge finger connection maintains socketability for system configuration. The edge finger connector is denoted as 'Slot 1 connector' in this and other documentation.

The entire enclosed product is called the Pentium® II Processor. The packaging technology and each of the physical elements of the product are referred to using accurate technical descriptions. This allows clear reference to the products as just a

processor. This is the model used in past packaging technologies like PGA, TCP, PQFP, DIP, etc.

S.E.C. Cartridge Terminology

- **Pentium® II Processor**
The new enclosed card packaging technology is called a "Single Edge Contact cartridge." This is similar to previous names for packaging technology such as PGA or TCP.
- **Processor card**
The green PCB (with or without components on it)
- **Processor core**
The silicon on the PLGA package on the PCB
- **Cover**
The plastic cover on the opposite side from the thermal plate.
- **Slot 1**
The slot that the S.E.C. cartridge plugs into, just as the Pentium® Pro processor uses Socket 3.
- **Retention mechanism**
Formerly 'retention module' the dual posts, etc. that holds the cartridge in place.
- **Thermal plate**
The heatsink attachment plate.
- **Heat sink supports**
The support pieces that are mounted on the mainboard to provide added support for heatsinks.

The L2 cache (TagRAM, PBSRAM) components keep standard industry names.

The Pentium® II Processor is the first product to utilize the S.E.C. cartridge technology and Slot 1 connector. Unless otherwise noted, any references to "Pentium® II Processor," "Pentium® II Processor/Slot 1 processor" or "Processor" will apply to both the Pentium® II Processor desktop processors.




Figure 1: Pentium® II Processor CPU with S.E.C. Cartridge

Accelerated Graphics Port (AGP or A.G.P.)

Typically, 3D graphics rendering requires a tremendous amount of memory, and demands ever increasing throughput speed as well. As 3D products for the personal computer become more and more popular, these demands will only increase. This will cause a rise in costs for both end users and manufacturers. Lowering these costs as well as improving performance is the primary motivation behind AGP. By providing a massive increase in the bandwidth available between the video card and the processor, it will assist in relieving some of these pressures for quite sometime.

Hardware Monitoring

Hardware monitoring allows you to monitor various aspects of your systems operations and status. These include features such as CPU temperature, voltage and fan RPM's.

Desktop Management Interface (DMI)

DMI, or Desktop Management Interface, is a BIOS level method for monitoring specific BIOS related hardware features. It allows the BIOS to collect and store information specific to the system, so that vendors and system integrators will have greater access to information regarding system configuration and design. This allows for better troubleshooting, migration planning, and upgradeability decision making.

EP-61EXA-A Form-Factor

The EPoX EP-61EXA-A is designed with Micro ATX form factor - the latest industry standard of chassis. The Micro ATX form factor is essentially a Baby-AT baseboard rotated 90 degrees within the chassis enclosure and a new mounting configuration for the power supply. With these changes the processor is relocated away from the expansion slots, allowing them all to hold full length add-in cards. ATX defines a double height aperture to the rear of the chassis which can be used to host a wide range of onboard I/O. Only the size and position of this aperture is defined, allowing PC manufacturers to add new I/O features (e.g., TV input, TV output, joystick, modem, LAN, audio, etc.) to systems. This will help systems integrators differentiate their products in the marketplace, and better meet your needs.

- By integrating more I/O down onto the board and better positioning the hard drive and floppy connectors material cost of cables and add-in cards is reduced.
- By reducing the number of cables and components in the system, manufacturing time and inventory holding costs are reduced and reliability will increase.
- By using an optimized power supply, it's possible to reduce cooling costs and lower acoustical noise. An ATX power supply, which has a side-mounted fan, allows direct cooling of the processor and add-in cards making a secondary fan or active heatsink unnecessary in most system applications.





Figure 2. Summary of Micro ATX chassis features

I/O Shield Connector

The EP-61EXA-A is equipped with an I/O back panel. Please use the appropriate I/O shield (figure 3).



Power-On/Off (Remote)

The EP-61EXA-A has a single 20-pin connector for ATX power supplies. For ATX power supplies that support the **Remote On/Off** feature, this should be connected to the systems front panel for system Power On/Off button. The systems power On/Off button should be a momentary button that is normally open.

The EP-61EXA-A has been designed with 'Soft Off' functions. You can turn Off the system from one of two sources. The first is the front panel Power On/Off button, and the other is the 'Soft Off' function coming from the EP-61EXA-A's onboard circuit controller, that can be controlled by the operating system. Windows 95 will control this when the user clicks that they are ready to Shutdown the system.




Figure 4 Simple ATX Power ON/OFF Controller

System Block Diagram




Figure 5 System Block Diagram

Section 2
FEATURES

EP-61EXA-A Features:

- EP 61EXA-A is based on the Pentium® II Processor operating at 233 ~ 333 MHz on Slot 1. The board is configured by an DIP Switch to match your CPU clock speed.
- Designed with Intel's 82443 EX AGPset
- Supports up to 256MB of DRAM (minimum of 8 MB on board (please see Section 3.2).
- Supports (2) 16 bit ISA slots, (2) 32 bit PCI slots, 1 AGP slot and provides (2) independent high performance PCI IDE interfaces capable of supporting PIO Mode 3/4 and Ultra DMA 33 devices. The EP 61EXA-A supports (2) PCI Bus Master slots and a jumperless PCI INT# control scheme which reduces configuration confusion when plugging in PCI cards.
- Supports ATA/PI (e.g. CD-ROM) devices on both Primary and Secondary IDE interfaces.
- Designed with Winbond W83977TF Multi I/O: 1 floppy port, 1 parallel port (EPP/ECP) and (2) serial ports 16550 Fast UART.
Note: Japanese "Floppy 3 mode" is also supported.
- Includes a PS/2 mouse connector.
- Allows use of a PS/2 or AT keyboard.
- Features Award Plug & Play BIOS. With Flash Memory you can always upgrade to the current BIOS as they are released. <http://www.epox.com> please visit our Technical Support section for the latest updates.
- EP 61EXA-A utilizes a Lithium battery which provides environmental protection and longer battery life.
- Supports the Universal Serial Bus (USB) connector. The onboard PIIK4 chip provides the means for connecting PC peripherals such as keyboards, joysticks, telephones, and modems.

- Built-in ATX 20-pin power supply connector
- Software power down when using Windows® 95/98
- Supports ring-in feature: remote power on through external modem, allows system to be turned on remotely
- Resume by Alarm: Allows your system to turn on at a preselected time
- Power Loss Recovery: In the event of a power outage your system will automatically turn itself back on without user intervention
- Supports CPU Hardware sleep and SMM (System Management Mode)
- Supports Desktop Management Interface (DMI) facilitating the management of desktop computers, hardware and software components and peripherals, whether they are stand alone systems or linked into networks: option
- Built-in WOL (Wake On Lan) Connector
- Built-in SB-Link Connector
- Supports YAMAHA Audio interface (YMF-715B-S)

Section 3

INSTALLATION

EP 61EXA-A Detailed Layout




Figure 1

Easy Installation Procedure

Easy Installation Procedure

The following must be completed before powering on your new system

- 3.1 Configure DIP Switch to match your hardware
- 3.2 Install memory chips
- 3.3 Install Pentium II Processor
- 3.4 Device Connectors

Section 3-1 Configure DIP Switch


EPoX designs this motherboard with a DIP Switch to make your installation fast and easier

The following will describe all of the DIP Switch that you are required to set before moving on to step 3.2

Note. The DIP Switch as depicted as shown (Figure 1) in their correct physical orientation

SW1

ON ➔



SW1				CPU
1	2	3	4	
ON			ON	233
	ON	ON	ON	266
	ON		ON	300
		ON	ON	333

Section 3-2


System Memory Configuration

Memory Layout

The EP-61EXA-A supports 2 68-pin DIMMs (Dual In-line Memory Module). The DIMMs can be either EDO (Enhanced Data Out) or SDRAM (Synchronous DRAM).

- DIMM SDRAM may be 83MHz (12ns), 100MHz (10ns) or 120MHz (8ns) bus speed.
- If you use both 50ns and 60ns memory you must configure your BIOS to read 60ns.
- When using Synchronous DRAM we recommend using the 4 clock waitstate over the 2 clock.
- **Fast Page Mode DRAM (FPM) is not supported by the EX AGPset. Only EDO and SDRAM are supported.**

Figure 2 and Table 1 show several possible memory configurations using both SDRAM and EDO memory.



Total Memory	DIMM 1 (Bank 0)	DIMM 2 (Bank 1)
256MB Maximum	EDO/SDRAM* 8MB, 16MB, 32MB, 64MB, 288MB X	EDO SDRAM* 8MB, 16MB, 32MB, 64MB, 128MB X
= 288MB Maximum	EDO/SDRAM* 8MB, 16MB, 32MB, 64MB, 288MB X	None


* SDRAM only supports 8, 16, 32, 64, 128MB DIMM modules

Table 1

DIMM Module Installation

Figure 5 displays the notch marks and what they should look like on your DIMM memory module.


DIMMs have 168 pins and two notches that will match with the onboard DIMM socket. DIMM modules are installed by placing the chip firmly into the socket at a 90 degree angle and pressing straight down (figure 6) until it fits tightly into the DIMM socket (figure 7).




↑
LEFT KEY ZONE
(UNBUFFERED)

↑
CENTER KEY ZONE
3.3V DRAM

Figure 5

*Figure 5*

DIMM Module clip before installation

*Figure 6*

DIMM Module clip after installation

To remove the DIMM module simply press down both of the white clips on both sides and the module will be released from the socket

Section 3-3

Installing a Pentium II Processor

The EP-61EXA-A uses the Single Edge Contact (SEC) slot for a Pentium II processor packaged in an SEC cartridge. The SEC slot is not compatible with other non Pentium II processors.

Please have ready the following list of components so that we may install the processor onto the motherboard.

- 1 Heat sink support (top/bottom piece)
- 2 Pentium II processor heat sink
- 3 Into Pentium II Processor

OK, now that you have all of your components ready, we can start.

❶ First, please refer to figure 8 below and follow the direction to lift up the fixed foldable pentium® II Retention Mechanism. This pre-installed device is designed for you to install Pentium® II CPU more easier and to avoid any damage on the board due to overtightening the four screws.

❷ One thing must be kept in your mind that please make sure to lift up/right the foldable parts of the Retention module to fit and install CPU properly.



Figure 8

Now we are going to install the heatsink support base piece (figure 9) onto the motherboard. There is both a large and small hole (figure 10) so that the base will only fit in one direction. This piece needs to be pushed into the holes firmly until it is seated.

Now we are ready to install the SEC Cartridge (Pentium II Processor) into the Retention Module. The SEC Cartridge is mounted by sliding the SEC Cartridge into the Retention Module and letting it slide all the way down. Once it reaches the


bottom make sure you press firmly on SEC cartridge to firmly secure into the Slot 1 Socket

Now we need to secure the heatsink with the top half of the support Figure 11. Take the top piece of the support and slide it into the bottom fin (Figure 11) on the heatsink and then push forward until it clips into the bottom base (figure 9) that is already there (Figure



Figure 9

Figure 9 shows the layout of Slot 1 and the holes for mounting the Heatsink base piece (figure 8)



Large Hole for Heat Sink Base

Small Hole for Heat Sink Base

Figure 10




Figure 11

Section 3-4

Device Connectors

Please install the motherboard into the chassis

Now that your motherboard is installed you are ready to connect all your connections (figure 12)




Figure 12

- J2 Chassis Panel Connector
 - Keylock, Speaker, Reset
- J3 IR Conn, TB, LED, HDD, LED, POWER ON
- J4 CPU Fan Power
 - A plug-in for the CPU Fan Power
- J6 Chassis Fan Power
 - A plug-in for the chassis Fan Power
- J7 WOL (Wake on Lan) Connector
- J8 SB Link Connector
- IDE1 Primary IDE
- IDE2 Secondary IDE
- FDD1 Floppy Controller
- CD1 MITSUMI CD ROM Audio in
- CD2 SONY CD ROM Audio in
- CD3 Panasonic CD-ROM Audio in

Section 3-4**Device Connectors (continued)**

J2	1	■	KeyLock Keyboard lock switch & Power LED connector	
		■	1 Power LED(+ 4 Keylock	
		■	2 N/C 5 GND	
		■	3 GND	
		■		
		■		
		■		
		■		
		■		
		■		
	1	■	Speaker Connect to the system's speaker for beeping	
		■	1 Speaker 3 GND	
		■	2 N/C 4 GND	
		■		
		■		
		■		
		■		
		■		
		■		
		■	Reset Closed to restart system	
J3	1	■	IR Connector	
		■	1 VCC 4 GND	
		■	2 NC 5 IRTX	
		■	3 IRRX	
		■		
		■		
		■		
		■		
		■		
		■		
	+	■	IDE LED indicator LED ON when Onboard PCI IDE Hard disks is activate	
	+	■	Turbo LED indicator LED ON when higher speed is selected	
		■		
		■		
		■	Power On Off This is connected to the power button on the case	
		■	Using the Soft Off by Pwr BTTN feature you can choose either	
			Instant Off (turns system off immediately or 4 sec delay you need to	
			hold the button down for 4 seconds before the system turns off) When	
			the system is in 4 sec delay mode, EPoX has added a special feature to	
			make the system go into suspend mode when the button is pressed	
			momentarily	

Section 4**AWARD BIOS SETUP****BIOS Instructions**

Award's ROM BIOS provides a built-in Setup program which allows user to modify the basic system configuration and hardware parameters. The modified data will be stored in a battery-backed CMOS, so that data will be retained even when the power is turned off. In general, the information saved in the CMOS RAM will stay unchanged unless there is a configuration change in the system, such as hard drive replacement or a device is added.

It is possible for the CMOS battery to fail, this will cause data loss in the CMOS only. If this does happen you will need to reconfigure your BIOS settings.

To enter the Setup Program

Power on the computer and press the key immediately, this will bring you into the BIOS CMOS SETUP UTILITY.

ROM PC BIOS (2A69KPA9)
CMOS SETUP UTILITY
AWARD SOFTWARE, INC.

STANDARD CMOS SETUP	SUPERVISOR PASSWORD
BIOS FEATURES SETUP	USER PASSWORD
CHIPSET FEATURES SETUP	DE HDD AUTO DETECTION
POWER MANAGEMENT SETUP	HDD LOW LEVEL FORMAT
PWP/PC CONFIGURATION	SAVE & EXIT SETUP
INTEGRATED PERIPHERALS	EXIT WITHOUT SAVING
LOAD SETUP DEFAULTS	
ESC QUIT	↑ ↓ → SELECT ITEM
F10 Save & Exit Setup	(Shift)F2 Change Color
Time, Date, Hard Disk Type	

Figure 1 CMOS Setup Utility

The menu displays all the major selection items. Select the item you need to reconfigure. The selection is made by moving the cursor (press any direction key) to the item and pressing the Enter key. An on-line help message is displayed at the bottom of the screen as the cursor is moved to various items which provides a better understanding of each function. When a selection is made, the menu of the selected item will appear so that the user can modify associated configuration parameters.

4-1 Standard CMOS Setup

Choose "Standard CMOS Setup" in the CMOS SETUP UTILITY Menu (Figure 2). The Standard CMOS Setup allows the user to configure system settings such as the current date and time, type of hard disk drive installed, floppy drive type, and display type. Memory size is auto-detected by the BIOS and displayed for your reference. When a field is highlighted (use direction keys to move the cursor and the <Enter> key to select), the entries in the field can be changed by pressing the <PgDn> or the <PgUp> key.

ROMPC15A BIOS(2A69KPA9)
STANDARD CMOS SETUP
AWARD SOFTWARE, INC.

Date (mm dd yy) Wed. Apr 17 1996									
Time (hh:mm:ss) 11:57:24									
HARD	TYPE	SIZE	CYLS	HEAD	PRECOMP	LANDZONE	SECTORS	MODE	
Primary Master	Auto	0	0	0	0	0	0	Auto	
Primary Slave	Auto	0	0	0	0	0	0	Auto	
Secondary Master	Auto	0	0	0	0	0	0	Auto	
Secondary Slave	Auto	0	0	0	0	0	0	Auto	
<div> <div> Drive A: 1.44M, 3.5 in Drive B: None Floppy 2 Mode Support Disabled Video EGA/VGA Halt On All Errors </div> <div> Basic Memory 640K Extended Memory 3,744K Other Memory 784K <hr/> Total Memory 7,168K </div> </div>									
ESC Quit		↑ ↓ →		Select Item		F10/PgDn		Modify	
F1 Help		(Shift) F1		Change Color					

Figure 2 Standard CMOS Setup

NOTE If the hard disk Primary Master/Slave and Secondary Master/Slave are set to Auto, then the hard disk size and model will be auto-detected.

NOTE: The "Halt On " field is used to determine when to halt the system by the BIOS if an error occurs.

NOTE Floppy 3 mode support is a mode used to support a special 3.5" drive used in Japan. This is a 3.5" disk that stores only 1.2 MB, the default setting for this is disabled.

4-2 BIOS Features Setup

Selecting the "BIOS FEATURES SETUP" option in the CMOS SETUP UTILITY menu allows users to change system related parameters in the displayed menu. This menu shows all of the manufacturer's default values for the EP-61EXA-A.

Pressing the [F1] key will display a help message for the selected item.

ROM PCI/LBA BIOS (2869JMMK) BIOS FEATURES SETUP AWARD SOFTWARE, INC			
Virus Warning	: Disabled	Video BIOS Shadow	: Enabled
CPU Internal Cache	: Enabled	C0000-CBFFF Shadow	: Disabled
External Cache	: Enabled	CC000-CFFFF Shadow	: Disabled
Quick Power On Self Test	: Enabled	D0000-D3FFF Shadow	: Disabled
Boot Sequence	: A C SCSI	D4000-D7FFF Shadow	: Disabled
Swap Floppy Drive	: Disabled	D8000-DBFFF Shadow	: Disabled
Boot Up Floppy Seek	: Enabled	DC000-DFFFF Shadow	: Disabled
Boot Up NumLock Status	: On		
Boot Up System Speed	: High		
Gate A20 Option	: Fast		
TypeMatic Rate Setting	: Disabled		
TypeMatic Rate (Chars/Sec)	: 6		
TypeMatic Delay (Msec)	: 250		
Security Option	: Setup		
PCI/VGA Palette Snoop	: Disabled		
OS Select For DRAM > 64MB	: Non-OS2		
		ESC Quit	+< = Select Item
		F1 Help	PG/BD/+/- Modify
		F5 Old Values	(Shift)F2 Color
		F7 Load Setup Defaults	

Figure 3 BIOS Features Setup

Virus Warning: During and after the system boots up, any attempt to write to the boot sector or partition table of the hard disk drive will halt the system and an error message will appear. You should then run an anti-virus program to locate the virus. Keep in mind that this feature protects only the boot sector, not the entire hard drive. The default value is Disabled.

Enabled: Activates automatically when the system boots up causing a warning message to appear when anything attempts to access the boot sector

Disabled: No warning message will appear when anything attempts to access the boot sector

Note: Many disk diagnostic programs that access the boot sector table can trigger the virus warning message. If you plan to run such a program, we recommend that you first disable the virus warning.

CPU Internal Cache This controls the status of the processor's internal cache area

The default is Enabled

Enabled: This activates the processor's internal cache thereby increasing performance

Disabled: This deactivates the processor's internal cache thereby lowering performance

External (L2) Cache This controls the status of the external L2 cache area

The default is Enabled

Enabled: This activates the CPU L2 cache thereby increasing performance

Disabled: This deactivates the CPU L2 cache thereby lowering performance

Quick Power On Self Test This category speeds up the Power On Self Test (POST)

The default is Enabled

Enabled: This setting will shorten or skip of the items checked during POST

Disabled: Normal POST

Boot Sequence This category determines which drive is searched first by the O/S (Operating System)

The default is A C SCSI

The following is your list of options

[A C SCSI] [C A SCSI] [C CD-ROM A] [CD-ROM C A]

[D A CD-ROM] [E A CD-ROM] [F A CD-ROM] [SCSI A C]

[SCSI C A] [C Only]

Swap Floppy Drive This will swap your physical drive letters A & B if you are using two floppy disks.
The default is Disabled.

Enabled: Floppy A & B will be swapped under the OS.

Disabled: Floppy A & B will be not swapped.

Boot Up Floppy Seek During Power On Self Test (POST) BIOS will determine if the floppy disk drive installed is 40 or 80 tracks. Only 720K type is 40 tracks while 720K, 1.2MB and 1.44MB are all 80 tracks.
The default is Enabled.

Enabled: The BIOS will search the floppy disk drive to determine if it is 40 or 80 tracks.

Disabled: The BIOS will not search for the type of floppy disk drive by track number.

NOTE: BIOS can not tell the difference between 720K, 1.2MB and 1.44MB drive types as they are all 80 tracks.

Boot Up NumLock Status This controls the state of the NumLock key when the system boots.
The default is On.

On: The keypad acts as a 10-key pad.

Off: The keypad acts like the cursor keys.

Boot Up System Speed This controls the initial system speed of the computer.
The default is High.

High: This setting sets the computer into normal operation mode.

Low: This setting sets the computer into a slower operating mode. Some add-in peripherals or old software may require this setting. Using CTRL+ALT+F1 will switch you back into high speed mode.

Gate A20 Option This refers to the way the system addresses memory above 1MB extended memory.
The default is Fast.

Normal: The A20 signal is controlled by the keyboard controller or chipsets hardware.

Fast: The A20 signal is controlled by Port 92 or chipset specific method.

Typematic Rate Setting This determines the keystrokes repeat rate.
The default is Disabled.

***Enabled:** Allows typematic rate and typematic delay programming.*

***Disabled:** The typematic rate and typematic delay will be controlled by the keyboard controller in your system.*

Typematic Rate (Chars/Sec) This is the number of characters that will be repeated by a keyboard press.
The default is 6.

6	6 characters per second	8	8 characters per second
10	10 characters per second	12	12 characters per second
15	15 characters per second	20	20 characters per second
24	24 characters per second	30	30 characters per second

Typematic Delay (msec) This setting controls the time between the first and the second character displayed by typematic auto-repeat.
The default is 250.

250	250 msec
500	500 msec
750	750 msec
1000	1000 msec

Security Option This category allows you to limit access to the System and Setup, or just to Setup.
The default is Setup.

***System:** The system will not boot and the access to Setup will be denied if the correct password is not entered at the prompt.*

***Setup:** The system will boot, but the access to Setup will be denied if the incorrect password is not entered at the prompt.*

PCI VGA Palette Snoop This field controls the ability of a primary PCI VGA controller to share a common palette (When a snoop write occurs) with an ISA video card.
The default is Disabled.

***Enabled:** If an ISA card is connected to a PC's VGA card via the VESA connector, and that ISA card connects to a VGA monitor, then that ISA card uses the RAMDAC of the PCI card.*

***Disabled:** Disables the VGA card Palette Snoop function.*

OS Select For DRAM = 64MB Some operating systems require special handling. Use this option only if your system has greater than 64MB of memory. The default is Non-OS2.

OS2 Select this if you are running the OS/2 operating system with greater than 64MB of RAM.

Non-OS2 Select this for all other operating systems and configurations.

Video BIOS Shadow This option allows video BIOS to be copied into RAM.

Video Shadowing will increase the video performance of your system.

The default is Enabled.

Enabled: Video shadow is enabled.

Disabled: Video shadow is disabled.

C8000 C8FFF Shadow

CC000 CFFFF Shadow

D0000 D3FFF Shadow

D4000 D7FFF Shadow

D8000 DBFFF Shadow

DC000 DFFFF Shadow

These categories determine whether ROMs from option cards will be copied into RAM. This will be in 16K byte or 32K byte units, and the size will depend on chipset of the option card.

Enabled: Optional shadow is enabled.

Disabled: Optional shadow is disabled.

4-3 Chipset Features Setup

Choose the "CHIPSET FEATURES SETUP" in the CMOS SETUP UTILITY menu to display following menu

ROM PCI/ISA BIOS (2A69JHWMC)
CHIPSET FEATURES SETUP
AWARD SOFTWARE, INC.

Auto Configuration	Enabled	SDRAM CAS latency Time	2
DRAM Speed Selection	60ns		
RA Wait State	Fast		
EDO RAS# To CAS# Delay	3		
EDO RAS# Precharge Time	3		
EDO DRAM Read Burst	x222		
EDO DRAM Write Burst	x222		
DRAM Data Integrity Mode	Mem ECC		
CPU-To-PCI IDE Posting	Enabled		
System BIOS Cacheable	Disabled		
Video BIOS Cacheable	Disabled		
Video RAM Cacheable	Disabled		
8 Bit I/O Recovery Time	3		
16 Bit I/O Recovery Time	2		
Memory Hole At 15M-16M	Disabled		
Passive Release	Enabled	ESC	Quit F4 : Select Item
Delayed Transaction	Enabled	F1	Help F5, PD/+, : Modify
AGP Aperture Size (MB)	8	F5	Old Values (Shift F2 : Color
SDRAM RAS to CAS Delay	Fast	F7	Load Setup Defaults
SDRAM RAS Precharge Time	Fast		

Figure 4 Chipset Features Setup

Auto Configuration This selects predetermined optimal values of the chipset parameters

The default is **Enabled**

Enabled This enables auto-configuration and provides the option to select predefined timing modes

Disabled This allows the user to specify DRAM timing parameters

Note If you exceed the performance characteristics of memory in your system it will result in lockups, crashes and other problematic system operations.

EDO DRAM Speed Selection This value must correspond to the speed of the DRAM installed in your system

The default is 60ns

50ns. *(Faster Burst Wait State, for 50ns EDO DRAM)*

60ns *(Slower Burst Wait State, for 60ns Fast Page Mode EDO DRAM)*

MA Additional Wait State This allows the option to insert an additional wait state before the beginning of a memory read. Use of this option may be required to achieve compatibility with some system configurations.

The default is Slow.

Fast. *inserts no wait state*

Slow. *inserts one wait state for the memory cycle.*

EDO RAS# to CAS# Delay Allows you to insert a timing delay between the CAS and RAS strobe signals used when DRAM is written to, read from, or refreshed.

The default is 3.

2. *Faster performance.*

3. *Better reliability.*

EDO RAS# Precharge Time The precharge time is the number of cycles it takes for the RAS to accumulate its charge before EDO DRAM refresh. If insufficient time is allowed, refresh may be incomplete and the EDO DRAM may fail to retain data.

The default is 4.

3. *Time equals 3 host clocks*

4. *Time equals 4 host clocks*

EDO DRAM Read Burst (B/E/F) This setting will allow you to set the timing for burst mode reads from EDO DRAM. The lower the timing number the faster the system addresses the memory.

The default is x333.

x222 *Use of this option may cause conflicts with some system configurations.*

x333 *This is used for standard system configurations.*

EDO DRAM Write Burst (B/E/F) This setting will allow you to set the timing for burst mode writes to EDO DRAM. The lower the timing number the faster the system addresses the memory.

The default is x333.

x222. Use of this option may cause conflicts with some system configurations.

x333 This is used for standard system configurations.

DRAM Data Integrity Mode Use this option to configure the type of DRAM in your system.

The default is Non-ECC.

Non-ECC: If your memory is Non-ECC memory, choose this option.

ECC: If your memory is ECC memory, choose this option.

CPU-to-PCI IDE Posting This option allows the computer to post write cycles from the CPU to the PCI IDE interface. IDE accesses are posted in the CPU to PCI buffers for cycle optimization.

The default is Enabled.

Enabled: Enabled

Disabled: Disabled

System BIOS Cacheable This allows you to copy your BIOS code from slow ROM to fast RAM.

The default is Disabled.

Enabled: The option will improve system performance. However, if any program writes to this memory area, a system error may result.

Disabled: System BIOS non-cacheable.

Video BIOS Cacheable This option copies the video ROM BIOS to fast RAM (C0000h to C7FFFh).

The default is Enabled.

Enabled: Enables the Video BIOS Cacheable to speed up the VGA Performance.

Disabled: Will not use the Video BIOS Cacheable function.

Video RAM Cacheable This option allows the CPU to cache read/writes of the video RAM.

The default is Enabled.

Enabled: This option allows for faster video access.

Disabled: Reduced video performance.

8 Bit I/O Recovery Time This function allows you to set the wait state that is added to an 8 bit ISA instruction originated by the PCI bus.
The default is 2.

NA	No wait state	8	8 wait states
1	1 wait states	2	2 wait states
3	3 wait states	4	4 wait states
5	5 wait states	6	6 wait states
7	7 wait states		

16 Bit I/O Recovery Time This function allows you to set the wait state that is added to an 16 bit ISA instruction originated by the PCI bus.
The default is 2.

NA	No wait state	4	4 wait states
3	3 wait states	2	2 wait states
1	1 wait states		

Memory Hole at 15M-16M You can reserve this memory area for the use of ISA adaptor ROMs.
The default is Disabled.

Enabled: This field enables the main memory (15-16MB) to remap to ISA BUS.

Disabled: Normal Setting.

NOTE: If this feature is enabled you will not be able to cache this memory segment.

Passive Release This option allows access from the CPU to PCI bus to be active during passive release. Otherwise, the arbiter only accepts another PCI master access to local DRAM.
The default is Enabled.

Enabled: Enabled

Disabled: Disabled

Delayed Transaction This option allows the chipset to use its embedded 32-bit posted write buffer to support delay transactions cycles.
The default is Disabled.

Enabled: Select enabled to support PCI 2.1 specification

Disabled: Disabled

AGP Aperture Size The amount of system memory that the AGP card is allowed to share

The default is 4

- 4. 4MB of systems memory accessible by the AGP card.*
- 8. 8MB of systems memory accessible by the AGP card*
- 16. 16MB of systems memory accessible by the AGP card.*
- 32. 32MB of systems memory accessible by the AGP card.*
- 64. 64MB of systems memory accessible by the AGP card.*
- 128. 128MB of systems memory accessible by the AGP card*
- 256. 256MB of systems memory accessible by the AGP card*

SDRAM RAS# to CAS# Delay Allows you to insert a timing delay between the CAS and RAS strobe signals, used when SDRAM is written to read from or refreshed

The default is Fast

- Fast Provides faster memory performance*
- Slow Provides better memory compatibility.*

SDRAM Precharge Time The precharge time is the number of cycles it takes for the RAS to accumulate its charge before SDRAM refresh. If insufficient time is allowed, refresh may be incomplete and the SDRAM may fail to retain data.

The default is Fast

- Fast. Provides faster memory performance.*
- Slow Provides better memory compatibility.*

SDRAM CAS Latency Time This setting defines the CAI I timing parameter of the SDRAM in terms of clocks

The default is 3

- 2. Provides faster memory performance.*
- 3 Provides better memory compatibility.*

CPU Warning Temperature This is the temperature that the computer will respond to an overheating CPU

The default is disabled

- Enabled: Temperature is monitored on the CPU*
- Disabled This feature is turned off.*

Current CPU Temperature This is the current temperature of the CPU

Current Power FAN Speed The current power fan speed in RPMs

Current CPU FAN Speed The current CPU fan speed in RPMs

Current Chassis FAN Speed The current chassis fan speed in RPMs

CPU(V) The voltage level of the CPU

Note The hardware information above is not available for a mainboard without NS LM75/LM78 IC's

4-4 Power Management Setup

Choose the "POWER MANAGEMENT SETUP" in the CMOS SETUP UTILITY to display the following screen. This menu allows the user to modify the power management parameters and IRQ signals. In general, these parameters should not be changed unless it is absolutely necessary.

ROM BIOS AWARD BIOS (2A59)PAB POWER MANAGEMENT SETUP AWARD SOFTWARE, INC.

Power Management	User Define	***Reload Global Power Items***	
PM Control by APM	Yes	IRQ [3-7, 9-1], NMI	Enabled
Video off Method	VRH SYNC+Blank	Primary IDE 0	Disabled
Video off After	Standby	Primary IDE 1	Disabled
Modem Use IRQ	-	Secondary IDE 0	Disabled
Dorm Mode	Disabled	Secondary IDE 1	Disabled
Standby Mode	Disabled	Floppy Disk	Disabled
Suspend Mode	Disabled	Serial Port	Disabled
HDD Power Down	Disabled	Parallel Port	Disabled
Throttle Duty Cycle	62.5%		
USB Auto-Modem	Enabled		
Soft-off by PWR-BTIN	[PS]ON/OFF		
Resume by Alarm	Enabled		
Power Loss Recovery	Enabled		
Resume By Alarm	Enabled		
DR0 8 Clock Event	Disabled		
		Esc Quit	↑ ↓ → Select Item
		F1 Help	F10/F11 Modify
		F2 Old Values	(Shift) F2 Color
		F4 Load Setup Defaults	

Figure 5 Power Management Setup

You can only change the content of Dorm Mode, Standby Mode, and Suspend Mode when the Power Management is set to User Define.

Power Management Use this to select your Power Management selection.
The default is User define

***Disabled:** The system operates in NORMAL conditions (Non-GREEN), and the Power Management function is disabled.*

***Max. saving:** Maximum power savings. Inactivity period is 1 minute in each mode.*

***Min saving:** Minimum power savings. Inactivity period is 1 hour in each mode.*

***User define:** Allows user to define PM Timers parameters to control power saving mode.*

PM controlled APM This option shows whether or not you want the Power Management to be controlled the Advanced Power Management (APM).
The default is Yes

***Yes:** APM controls your PM*

***No:** APM does not control your PM*

Video Off Method This option allows you to select how the video will be disabled by the power management.
The default is V/H Sync + Blank

***V/H Sync + Blank:** System turns off vertical and horizontal synchronization ports and writes blanks to the video buffer.*

***DPMS:** Select this option if your monitor supports the Display Power Management Signaling (DPMS) standard of the Video Electronics Standards Association (VESA). Use the software supplied for your video subsystem to select video power management values.*

***Blank Screen:** System only writes blanks to the video buffer.*

Video Off After Tells you what time frame that the video will be disabled under current power management settings.
The default is Standby

***Standby:** Video powers off after time shown in standby mode setting.*

***Doze:** Video powers off after time shown in doze mode setting.*

***Suspend:** Video powers off after time shown in suspend mode setting.*

***N/A:** Video power off not controlled by power management.*

MODEM Use IRQ Name the interrupt request (IRQ) line assigned to the modem (if any) on your system. Activity of the selected IRQ always awakens the system.
Default is IRQ 3

0 No IRQ is used	3 IRQ 3
4 IRQ 4	5 IRQ 5
7 IRQ 7	9 IRQ 9
10 IRQ 10	11 IRQ 11

The EP-61EXA-A supports HDD Power Down, Doze and Standby power saving functions when using the Intel Pentium II Processor.
The default is Disabled.

Doze Mode: The "Doze" mode timer starts to count when no "PM events" have occurred.

Standby Mode When the standby mode timer times out, it will enter the standby mode and retain CPU at a slow working speed. The screen will be blanked out.

Suspend Mode This function works only when the Pentium II Processor is installed. The timer starts to count when "System Standby" mode timer is timed out and no "PM Events" are occurring. Valid range is from 1 minute up to 1 hour.

HDD Power Down HDD Standby timer can be set from 1 to 15 minutes.

VGA Active Monitor Use this option if your monitor has advanced power saving features.
The default is Enabled.

***Enabled:** Your monitor's power features will be included in power management.*

***Disabled:** Your monitor's power features will not be included in power management.*

Soft-Off by PWR-BT IN Use this to select your soft-off function.
The default is Instant Off.

***Instant Off:** Turns off instantly.*

***4 Second Delay:** Turns off after a 4 second delay. If momentary press of button, the system will go into Suspend Mode. Press again to take system out of Suspend Mode.*

Resume by Ring This option is used to set the remote ring in feature. This option is only available when Power Loss Recovery is Enabled.

The default is Enabled.

Enabled: The system can use remote ring in to wake the system up.

Disabled: The system cannot use remote ring in to wake system up.

Power Loss Recovery If the power to the system is cut off the system will turn itself back on with no user intervention.

The default is Enabled.

Enabled: The system will power back on after a power interruption.

Disabled: The system will stay off after a power interruption.

Resume by Alarm This option allows you to have the system turn on at a preset time each day or on a certain day. This option is only available when Power Loss Recovery is Enabled.

The default is Enabled.

Enabled: The system will turn on at the preset time.

Disabled: The system will not turn on until you turn it on.

Date of month) Alarm: This is how you set the date that the system will turn on. The default is 0.

0: Setting this to 0 will turn the system on everyday at the preset time.

1-31: Represents the day of the month that you need the system to turn on.

Time (hh mm ss) Alarm This sets the time that you need the system to turn on. The default is 08:00:00.

****Reload Global Timer Events ****

These options allow the user to reset the global power features timer if any of the enabled events occur.

IRQ [3-7, 9-15], NMI The default is Enable.

Primary IDE 0 The default is Disable.

Primary IDE 1 The default is Disable.

Secondary IDE 0 The default is Disable.

Secondary IDE 1 The default is Disable.

Floppy Disk The default is Disable.

Serial Port The default is Enable.

Parallel Port The default is Disable.

4-5 PNP/PCI Configuration

The PNP/PCI configuration program is for the user to modify the PCI/ISA IRQ signals when various PCI/ISA cards are inserted in the PCI or ISA slots.

WARNING: Conflicting IRQ's may cause the system to not find certain devices

DO NOT SET THE VALUES IN THIS PAGE
FOR THE AUTO SETUP
WARNING: PLEASE READ

PNP OS Installed Resources Controlled By Reset Configuration Data		NO Manual Disabled	PCI IDE IRQ Map To Primary IDE CHN Secondary IDE CHN	A B	PCIAUTO
IRQ-0	assigned to	Legacy ISA	Used MEM bus addr		N/A
IRQ-1	assigned to	Legacy ISA			
IRQ-2	assigned to	PC/ISA PaP			
IRQ-3	assigned to	PC/ISA PaP			
IRQ-4	assigned to	PC/ISA PaP			
IRQ-5	assigned to	PC/ISA PaP			
IRQ-6	assigned to	PC/ISA PaP			
IRQ-7	assigned to	PC/ISA PaP			
IRQ-8	assigned to	PC/ISA PaP			
IRQ-9	assigned to	PC/ISA PaP			
IRQ-10	assigned to	PC/ISA PaP			
IRQ-11	assigned to	PC/ISA PaP			
IRQ-12	assigned to	PC/ISA PaP			
IRQ-13	assigned to	PC/ISA PaP			
IRQ-14	assigned to	PC/ISA PaP			
IRQ-15	assigned to	PC/ISA PaP			
DMA-0	assigned to	PC/ISA PaP			
DMA-1	assigned to	PC/ISA PaP			
DMA-2	assigned to	PC/ISA PaP			
DMA-3	assigned to	PC/ISA PaP			
DMA-4	assigned to	PC/ISA PaP			
DMA-5	assigned to	PC/ISA PaP			
DMA-6	assigned to	PC/ISA PaP			
DMA-7	assigned to	PC/ISA PaP			

Esc. Quit
F1 Help
F5 Old Values
F7 Load Setup Defaults

↑ ↓ → Select Item
PGUP/DN +/- Modify
Shift F2 Color

Figure 6 PCI Configuration Setup

PNP OS Installed Do you have a PNP OS installed on your system. The default is No.

Yes Select if you are using a PNP OS

No Select if your OS does not support PNP

Resources Controlled By Who controlled the system PNP/PCI resources. The default is Manual.

Manual PNP Controls resources will be controlled manually. You can set which IRQ-X and DMA-X are assigned to PCI/ISA PNP or Legacy ISA Cards.

Auto If your ISA card and PCI card are all PNP cards, BIOS will assign the interrupt resource automatically.

Reset Configuration Data This setting allows you to clear ESCD data. The default is Disabled.

Disabled: Normal Setting.

Enabled: If you have plugged in some Legacy cards to the system and they were recorded into ESCD (Extended System Configuration Data), you can set this field to Enabled in order to clear ESCD.

PCI IDE IRQ Map To This item allows the user to configure the system for the type of IDE hard disk controller in use. By default, the BIOS assumes that the hard drive controller is an ISA device rather than a PCI controller. If you are using a PCI controller, then you will need to change this to specify which PCI slot has the controller and which PCI interrupt (A, B, C, or D) is associated with the connected IDE devices.

The default value is PCI AUTO. This will allow the system to automatically configure the IDE devices.




Figure 7. The Combination of PCIINT#lines

Used MEM base addr The Used MEM base addr (CB00, CC00, D000, D400, D800, DC00) and Used MEM Length (8K, 16K, 32K, 64K) are used to support some specific ISA Legacy cards with requested memory space below 1M address. Now with these two functions, users can define where the used memory address is located and its length of the legacy area that is used by the legacy device to avoid the memory space conflict. For example, if you select "D000" for Used MEM base addr and "16K" for Used MEM Length, that means the address region D000H-D3FFFH is occupied by ISA legacy cards, and thus BIOS will not assign this region for PnP/ISA and PCI cards.

The default is N/A.

4-6 Load Setup Defaults

The "LOAD SETUP DEFAULTS" function loads the system default data directly from ROM and initializes the associated hardware properly. This function will be necessary only when the system CMOS data is corrupted.

4-7 Integrated Peripherals

ROM PCI/ISA BIOS (2AG9JMWG) INTEGRATED PERIPHERALS AWARD SOFTWARE, INC.			
IDE HDD Block Mode	Enabled		
IDE Primary Master PIO	Auto		
IDE Primary Slave PIO	Auto		
IDE Secondary Master PIO	Auto		
IDE Secondary Slave PIO	Auto		
IDE Primary Master UDMA	Auto		
IDE Primary Slave UDMA	Auto		
IDE Secondary Master UDMA	Auto		
IDE Secondary Slave UDMA	Auto		
On-Chip Primary PCI IDE	Enabled		
On-Chip Secondary PCI IDE	Enabled		
USB Keyboard Support	= Disabled		
KBC Input clock	= 8 MHz		
Onboard FDC Controller	Enabled		
Onboard Serial Port 1	= Auto		
Onboard Serial Port 2	= Auto		
Onboard IR Controller	Disabled		
		Onboard Parallel Port	= 378/IRQ7
		Parallel Port Mode	ECP+EPP
		ECP Mode Use DMA	= 3
		EPP Mode Select	EPP1: 9
		ESC : Quit	↑↓ : Select Item
		F1 : Help	PG/PD, +/ - : Modify
		F5 : Old Values	Shift, F2 : Color
		F7 : Load Setup Defaults	

Figure 8 Integrated Peripherals

Note: If you do not use the Onboard IDE connector, then you will need to set Onboard Primary PCI IDE Disabled and Onboard Secondary PCI IDE Disabled.

Note: The Onboard PCI IDE cable should be equal to or less than 18 inches (45 cm.)

IDE HDD Block Mode IDE Block Mode allows the controller to access blocks of sectors rather than a single sector at a time

The default is Enabled

***Enabled** Enables IDE HDD Block Mode. Provides higher HDD transfer rates*

***Disabled** Disables IDE HDD Block Mode*

Onboard Primary PCI IDE The default value is Enabled

***Enabled** Enables Onboard IDE primary port.*

***Disabled** Disables Onboard IDE primary port*

Onboard Secondary PCI IDE

The default is Enabled

***Enabled** Enables Onboard IDE secondary port.*

***Disabled** Disables Onboard IDE secondary port*

IDE Primary Master PIO

The default is Auto

***Auto** BIOS will automatically detect the Onboard Primary Master PCI IDE HDD Accessing mode*

***Mode 0-4** Manually set the IDE Programmed interrupt mode*

IDE Primary Slave PIO

The default is Auto

***Auto** BIOS will automatically detect the Onboard Primary Slave PCI IDE HDD Accessing mode*

***Mode 0-4** Manually set the IDE Programmed interrupt mode*

IDE Secondary Master PIO

The default is Auto

***Auto** BIOS will automatically detect the Onboard Secondary Master PCI IDE HDD Accessing mode*

***Mode 0-4** Manually set the IDE Programmed interrupt mode*

IDE Secondary Slave PIO

The default is Auto

***Auto** BIOS will automatically detect the Onboard Secondary Slave PCI IDE HDD Accessing mode*

Mode 0-4 similarly to the IDE Programmed interrupt mode.

IDE Primary Master UDMA This allows you to select the mode of operation for the hard drive

The default is Auto

Auto. The computer will select the optimal setting.

Disabled. The hard drive will run in normal mode

IDE Primary Slave UDMA This allows you to select the mode of operation for the hard drive

The default is Auto

Auto. The computer will select the optimal setting.

Disabled. The hard drive will run in normal mode

IDE Secondary Master UDMA This allows you to select the mode of operation for the hard drive

The default is Auto

Auto. The computer will select the optimal setting.

Disabled. The hard drive will run in normal mode

IDE Secondary Slave UDMA This allows you to select the mode of operation for the hard drive

The default is Auto

Auto. The computer will select the optimal setting.

Disabled. The hard drive will run in normal mode

USB Keyboard Support This controls the activation status of an optional USB keyboard that may be attached

The default is disabled

Enabled. Enable USB keyboard support.

Disabled. Disable USB keyboard support.

OnBoard Primary PCI IDE This option turns on and off the onboard primary IDE
The default is enabled

Enabled: This activates the primary PCI IDE.

Disabled: This disables the primary PCI IDE and frees up the resource

OnBoard Secondary PCI IDE This option turns on/off the onboard secondary IDE
The default is enabled

Enabled: This activates the secondary PCI IDE

Disabled: This disables the secondary PCI IDE and frees up its resources.

KBC input clock This sets the keyboard clock value
The default is 12 MHz

Options: 6, 8, 12, 16 are the available choices.

Onboard FDC Controller This controls the state of the onboard floppy controller
The default value is Enabled

Enabled: Enable the Onboard Winbond Chips floppy drive interface
COMANDLDR.

Disabled: Disable the Onboard Winbond Chip's floppy drive interface
COMANDLDR.

Onboard Serial Port 1 This field allows the user to configure the 1st serial port
The default is Auto

AUTO: Enable Onboard Serial port 1 and address is Auto adjusted

COM1: Enable Onboard Serial port 1 and address is 3F8H/IRQ4

COM2: Enable Onboard Serial port 1 and address is 2F8H/IRQ3

COM3: Enable Onboard Serial port 1 and address is 1E8H/IRQ4

COM4: Enable Onboard Serial port 1 and address is 2E8H/IRQ3

Disabled: Disable Onboard Winbond Chip's CHIP's Serial port 1

Onboard Serial Port 2 This field allows the user to configure the 2nd serial port
The default is Auto

AUTO: Enable Onboard Serial port 2 and address is Auto adjusted

COM1: Enable Onboard Serial port 2 and address is 1F8H/IRQ4

COM2: Enable Onboard Serial port 2 and address is 2F8H/IRQ3

COM3: Enable Onboard Serial port 2 and address is 1E8H/IRQ4

COM4: Enable Onboard Serial port 2 and address is 2E8H/IRQ3

Disabled: Disable Onboard Winbond Chip's CHIP's Serial port 2

Onboard IR Controller IrDA Controller

The default is Enabled

IR Address Select The port location of the IR controller

The default is 2E8H

IR Mode The mode of the IR controller

The default is IrDA

IR Transaction Delay

The default is Enabled

IR IRQ Select

The default is IRQ 10

IR Mode use DMA

The default is Disable

Onboard Parallel port This field allows the user to configure the LPT port

The default is 378H IRQ 7

378H Enable Onboard LPT port and address is 378H and IRQ7

278H Enable Onboard LPT port and address is 278H and IRQ5

3BCH Enable Onboard LPT port and address is 3BCH and IRQ7

Disabled: Disable Onboard Winbond Chip's LPT port.

Parallel Port Mode This field allows the user to select the parallel port mode

The default is ECP+EPP

Normal: Standard mode, IBM PC/AT Compatible bidirectional parallel port.

EPP Enhanced Parallel Port mode.

ECP Extended Capabilities Port mode.

EPP+ECP ECP Mode & EPP Mode

ECP Mode USE DMA This field allows the user to select DMA1 or DMA3 for the ECP mode

The default is DMA3

DMA1 This field selects the routing of DMA1 for the ECP mode

DMA3 This field selects the routing of DMA3 for the ECP mode

4-8 Change Supervisor or User Password

To change the password, choose the "SUPERVISOR PASSWORD or USER PASSWORD" option from the CMOS SETUP UTILITY menu and press Enter

NOTE Either "Setup" or "System" must be selected in the "Security Option" of the BIOS FEATURES SETUP menu.

- 1 If CMOS is corrupted or the option was not used, a default password stored in the ROM will be used. The screen will display the following message:

Enter Password

Press the [Enter] key to continue after the proper password is given

- 2 If the CMOS is corrupted or the option was used earlier and the user wishes to change the default password, the SETUP UTILITY will display a message and ask for a confirmation:

Confirm Password

- 4 After pressing the [Enter] key (ROM password if the option was not used or current password, user-defined password), the user can change the password and store new one in CMOS RAM. A maximum of 8 characters can be entered.

4-9 IDE HDD Auto Detection

The "IDE HDD auto detection" utility is a very useful tool, especially when you do not know which kind of hard disk type you are using. You can use this utility to detect the correct disk type installed in the system automatically. But now you can set HARD DISK TYPE to Auto in the STANDARD CMOS SETUP. You don't need the "IDE HDD AUTO DETECTION" utility. The BIOS will Auto detect the hard disk size and model on display during POST.




Figure 8 IDE HDD Auto Detection

NOTE HDD Modes

The Award BIOS supports 3 HDD modes: NORMAL, LBA & LARGE NORMAL mode.

Generic access mode in which neither the BIOS nor the IDE controller will make any transformations during accessing.

The maximum number of cylinders, head & sectors for NORMAL mode are

024	6 & 63
no Cylinder	024
x no Head	6
x no Sector	63
x no. per sector	5.2
	528 Megabytes

If user sets HDD to NORMAL mode, the maximum accessible HDD size will be 528 Megabytes even though its physical size may be greater than that.

LBA (Logical Block Addressing) mode A new HDD accessing method to overcome the 528 Megabyte bottleneck. The number of cylinders, heads & sectors shown in setup may not be the number physically contained in the HDD. During HDD accessing, the IDE controller will transform the logical address described by sector, head & cylinder into its own physical address inside the HDD. The maximum HDD size supported by LBA mode is 8.4 GigaBytes which is obtained by the following formula:

$$\begin{array}{rcl}
 \text{no. Cylinder} & & 1024 \\
 \times \text{no. Head} & & 255 \\
 \times \text{no. Sector} & & 63 \\
 \hline
 \text{no. bytes per sector} & & 512 \\
 \hline
 & & 8.4 \text{ GigaBytes}
 \end{array}$$

LARGE mode Extended HDD access mode supported by Award Software.

Some IDE HDDs contain more than 1024 cylinder without LBA support. In some cases, users do not want LBA. The Award BIOS provides another alternative to support these kinds of LARGE mode.

CYLIS	HEADS	SECTOR	MODE
120	16	59	NORMAL
560	32	59	LARGE

BIOS tricks DOS or other OS that the number of cylinders is less than 1024 by dividing it by 2. At the same time, the number of heads is multiplied by 2. A reverse transformation process will be made inside.

INT 13h in order to access the right HDD address.

Maximum HDD size

$$\begin{array}{rcl}
 \text{no. Cylinder} & & 1024 \\
 \times \text{no. Head} & & 32 \\
 \times \text{no. Sector} & & 63 \\
 \hline
 \text{no. bytes per sector} & & 512 \\
 \hline
 & & 1 \text{ GigaByte}
 \end{array}$$

Note: To support LBA or LARGE mode of HDDs, there must be some software involved. All the software is located in the Award HDD Service Routine (INT 13h). It may fail to access a HDD with LBA (LARGE) mode selected if you are running under a Operating System which replaces the whole INT 13h.

UNIX operating systems do not support either LBA or LARGE and must utilize the Standard mode. UNIX can support drives larger than 528MB.

4-10 HDD Low Level Format

Interleave Select the interleave number of the hard disk drive you wish to perform a low level format on. You may select from 1 to 8. Check the documentation that came with the drive for the correct interleave number, or select 0 for automatic detection.

Auto scan bad track This allows the utility to scan first then format by each track.

Start Press<Y>-to start low level format.

3-11 Save & Exit Setup

The "SAVE & EXIT SETUP" option will bring you back to the boot up procedure with all the changes you just recorded in the CMOS RAM.

3-12 Exit Without Saving

The "EXIT WITHOUT SAVING" option will bring you back to normal boot up procedure without saving any data into CMOS RAM.

All old data in the CMOS will not be destroyed

Section 5

ONLINE ACCESS:

DMI Access

DMI or desktop Management Interface is a feature that is able to auto-detect and record information about your computer system. This information is used by computing professionals to accurately determine your system configuration and to diagnose and resolve problems.

The computer's BIOS will detect and record as much information as it is able to, and will store that information in a special location in the BIOS.

The DMI configuration utility will allow system integrators to add information that the BIOS cannot detect such as model and brand of motherboard and other components. This information cannot be detected by the BIOS and must be added by the system integrator or vendor.



Figure 4. DMI Screen Shot

Appendix A:

A-1 MEMORY MAP

Address Range	Size	Description
[00000-7FFFF]	5.2K	Conventional memory
[80000-9FBFF]	27K	Extended Conventional memory
[9FC00-9FFFF]	K	Extended BIOS data area if PS/2 mouse is installed
[A0000-C7FFF]	60K	Available for Hi-DOS memory
[C8000-DEFFF]	96K	Available for Hi-DOS memory and adapter ROMs
[E0000-EEFFF]	60K	Available for UMB
[EF000-EFFFF]	4K	Video service routine for Monochrome & CGA adaptor
[F0000-F7FFF]	32K	BIOS CMOS setup utility
[F8000-FCFFF]	20K	BIOS runtime service routine (2)
[FD000-FDFFF]	4K	Plug and Play ESCD data area
[FE000-FFFFF]	8K	BIOS runtime service routine (1)

A-2 I/O MAP

[000-00F]	DMA controller (Master)
[020-02F]	INTEERRUPT CONTROLLER (Master)
[022-023]	CHIPSET control registers I/O ports
[040-05F]	TIMER control registers
[060-06F]	KEYBOARD interface controller '8042'
[070-07F]	RTC ports & CMOS I/O ports
[080-09F]	DMA register
[0A0-0BF]	INTERRUPT controller (Slave)
[0C0-0DF]	DMA controller (Slave)
[0FD-0FF]	MATH COPROCESSOR
[1FD-1FF]	HARD DISK controller
[278-27F]	PARALLEL port 2
[2B0-2DF]	GRAPHICS adapter controller
[2F8-2FF]	SERIAL port 2
[360-36F]	NETWORK ports
[378-37F]	PARALLEL port
[3B0-3BF]	MONOCHROME & PARALLEL port adapter
[3C0-3CF]	EGA adapter

[3D0-3DF]	CGA adapter
[3F0-3FF]	FLOPPY DISK controller
[3FB-3FF]	SERIAL port

A-3 TIMER & DMA CHANNELS MAP

TIMER MAP

TIMER Channel 0	System timer interrupt
TIMER Channel 1	DRAM REFRESH request
TIMER Channel 2	SPEAKER tone generator

DMA CHANNELS

DMA Channel 0	Available
DMA Channel 1	Onboard ECP Option
DMA Channel 2	FLOPPY DISK (SMC CHIP)
DMA Channel 3	Onboard ECP default
DMA Channel 4	Cascade for DMA controller 1
DMA Channel 5	Available
DMA Channel 6	Available
DMA Channel 7	Available

A-4 INTERRUPT MAP

NMI

Parity check error

IRQ H/W

0	System TIMER interrupt from TIMER 0 KEYBOARD output buffer full
2	Cascade for IRQ 8-15
3	SERIAL port 2
4	SERIAL port 1
5	PARALLEL port 2
6	FLOPPY DISK (SMC CHIP)
7	PARALLEL port 1
8	RTC clock
9	Available
10	Available
	Available
12	PS/2 Mouse
13	MATH coprocessor

-
- | | |
|---|---------------------------------|
| 4 | Onboard HARD DISK (IDE) channel |
| 5 | Onboard HARD DISK (IDE) channel |

A-5 RTC & CMOS RAM MAP

RTC & CMOS

00	Seconds
01	Second alarm
02	Minutes
03	Minutes alarm
04	Hours
05	Hours alarm
06	Day of week
07	Day of month
08	Month
09	Year
0A	Status register A
0B	Status register B
0C	Status register C
0D	Status register D
0E	Diagnostic status byte
0F	Shutdown byte
10	FLOPPY DISK drive type byte
11	Reserve
12	HARD DISK type byte
13	Reserve
14	Equipment type
15	Base memory low byte
16	Base memory high byte
17	Extension memory low byte
18	Extension memory high byte
19-1D	
2E-2F	
30	Reserved for extension memory low byte
31	Reserved for extension memory high byte
32	DATE CENTURY byte
33	INFORMATION FLAG
34-3F	Reserve
40-7F	Reserved for CHIPSET SETTING DATA

Appendix B:**B-1 POST CODES**

ISA POST codes are typically output to I/O port address 80h

POST (hex)	DESCRIPTION
0 02	Reserved
C0	Turn off OEM specific cache, shadow
03	1 Initialize ISA registers (EISA BIOS only) 2 Initialize all the standard devices with default values Standard devices includes DMA controller (8237) Programmable Interrupt Controller (8259) Programmable Interval Timer (8254) PIC chip
04	Reserved
05	1 Keyboard Controller Self-Test
06	2 Enable Keyboard Interface
07	Reserved
08	Verifies CMOS's basic R/W functionality
C	Auto-detection of onboard DRAM & Cache
C5	Copy the BIOS from ROM into E0000-FFFF shadow RAM so that POST will go faster
08	Test the first 256K DRAM
09	OEM specific cache initialization, if needed,
0A	1 Initialize the first 32 interrupt vectors with corresponding interrupt handlers outside NT numbers from 33-120 with Dummy (Spurious Interrupt Handler) c Issue CPU ID instruction to identify CPU type 3 Early Power Management initialization (OEM specific)
0B	Verify the RTC time is valid or not 2 Detect bad battery 3 Read CMOS data into BIOS stack area 4 PoP initializations including (PoP BIOS only) Assign CSN to PoP ISA card Create resource map from ESCD 5 Assign IO & Memory for PCI devices (PC BIOS only)

0C	Initialization of the BIOS Data Area (40:00 - 40:FF)
0D	1. Program some of the Chipset's value according to Setup. (Early Setup Value Program)
	2. Measure CPU speed for display & decide the system clock speed.
	3. Video initialization including Monochrome, CGA, EGA/VGA. If
no display device	found, the speaker will beep.
0E	1. Test video RAM (If Monochrome display device found)
	2. Show messages including
	- Award Logo, Copyright string, BIOS Data code & Part No.
	- OEM specific sign on messages.
	- Energy Star Logo (Green BIOS ONLY)
	- CPU brand, type & speed.
	- Test system BIOS checksum (Non-Compress Version only)
0F	DMA channel 0 test.
10	DMA channel 1 test.
11	DMA page registers test.
12-13	Reserved.
14	Test 8254 Timer 0 Counter 2.
15	Test 8259 interrupt mask bits for channel 1.
16	Test 8259 interrupt mask bits for channel 2.
17	Reserved.
19	Test 8259 functionality.
1A-1D	Reserved.
1E	If EISA NVM checksum is good, execute EISA initialization. (EISA BIOS only)
1F-29	Reserved.
30	Detect Base Memory & Extended Memory Size.
31	1. Test Base Memory from 256K to 640K.
	2. Test Extended Memory from 1M to the top of memory.
32	1. Display the Award Plug & Play BIOS Extension message. (PnP BIOS only)
	2. Program all onboard super I/O chips (if any) including COM ports, LPT ports, FDD port ... according to setup value.
33-3B	Reserved.
3C	Set flag to allow users to enter CMOS Setup Utility.
3D	1. Initialize Keyboard.
	2. Install PS2 mouse.

3E	Try to turn on Level 2 cache. Notes: Some chipset may need to turn on the L2 cache in this stage. But usually, the cache is turn on later in POST 61h.
3F-40	Reserved.
BF	1. Program the rest of the Chipset's value according to Setup. (Later Setup Value Program)
41	2. If auto-configuration is enabled, program the chipset with pre-defined Values.
42	Initialize floppy disk drive controller.
43	Initialize Hard drive controller.
45	If it is a PnP BIOS, initialize serial & parallel ports
44	Reserved.
45	Initialize math coprocessor.
46-4D	Reserved.
4E	If there is any error detected (such as video, kb...), show all error messages on the screen & wait for user to press <F1> key.
4F	1. If password is needed, ask for password. 2. Clear the Energy Star Logo. (Green BIOS only)
50	Write all CMOS values currently in the BIOS stack area back into the CMOS.
51	Reserved.
52	1. Initialize all ISA ROMs. 2. Later PCI initializations. (PCI BIOS only) - assign IRQ to PCI devices. - initialize all PCI ROMs 3. PnP Initializations. (PnP BIOS only) - assign IO, Memory, IRQ & DMA to PnP ISA devices. - initialize all PnP ISA ROMs. 4. Program shadows RAM according to Setup settings. 5. Program parity according to Setup setting. 6. Power Management Initialization. - Enable/Disable global PM. - APM interface initialization.
53	1. If it is NOT a PnP BIOS, initialize serial & parallel ports 2. Initialize time value in BIOS data area by translate the RTC time value into a timer tick value.
60	Setup Virus Protection. (Boot Sector Protection) functionality according to Setup setting.

61	<ol style="list-style-type: none"> 1. Try to turn on Level 2 cache. <p>Note: If L2 cache is already turned on in POST 3D, this part will be skipped.</p> <ol style="list-style-type: none"> 2. Set the boot up speed according to Setup setting. 3. Last chance for Chipset initialization. 4. Last chance for Power Management initialization. (Green BIOS only) 5. Show the system configuration table.
62	<ol style="list-style-type: none"> 1. Setup daylight saving according to Setup value. 2. Program the NUM Lock, typematic rate & typematic speed according to Setup setting.
63	<ol style="list-style-type: none"> 1. If there is any changes in the hardware configuration, update the ESCD information. (PnP BIOS only) 2. Clear memory that have been used. 3. Boot system via INT 19H.
FF	System Booting. This means that the BIOS already pass the control right to the operating system.

B-2 Unexpected Errors:

POST (hex)	DESCRIPTION
B0	If interrupt occurs in protected mode.
B1	Unclaimed NMI occurs.0

Appendix C

NOTE:

The "LOAD SETUP DEFAULTS" function loads the system default data directly from ROM and initializes the associated hardware properly. This function will be necessary when you accept this motherboard, or the system CMOS data is corrupted.

ROMPCI/ISA BIOS(2A69KPA9)
CMOS SETUP UTILITY
AWARD SOFTWARE, INC.

STANDARD CMOS SETUP	SUPERVISOR PASSWORD
BIOS FEATURES SETUP	USER PASSWORD
CHIPSET FEATURES SETUP	IDE HDD AUTO DETECTION
POWER MANAGEMENT SETUP	HDD LOW LEVEL FORMAT
PNP/PCI CONFIGURATION	Load SETUP Default (Y/N)? Y
INTEGRATED PERIPHERALS	SETUP SAVING
LOAD SETUP DEFAULTS	
ESC: QUIT ↑ ↓ → : SELECT ITEM	
F10 Save & Exit Setup (Shift)F2 : Change Color	
Load Setup Defaults Except Standard COMS SETUP	

LOAD SETUP DEFAULTS